Temperature Controllers

Model **TEC-9400** 1/16 DIN



Model TEC-9400 1/16 DIN Temperature Controller



Design Features

- $* 1/16 DIN size 48 mm \times 48 mm$
- * Fuzzy Logic PID Autotune heat and cool control
- * Universal input, field configurable (Type J T/C default, PT100, mA, V) with high accuracy 18-bit D-A
- * Countdown display
- * RS 485 and Analog Retransmission Available
- * Micro USB Programming Port
- * Fast sampling rate (200 msec)

- * Manual control & auto-tune function
- * Wide range of alarm mode selection
- * Lockout protection
- * Bumpless transfer during failure mode
- * Soft-start ramp & dwell timer
- * Bright LCD display using NFPA/IEC standard colors
- * High performance with low cost

Agency Approvals:





RoHS, REACH, WEEE

File #: E244198

Hardware Code: TEC-9400 -

1 2 3 4 5 6 7 8

A Part Number based on the hardware code and any software pre-programming will be issued at time of order.

Power Input BOX 1

- **4** = 90-250 VAC
- 5 = 11-40 VDC / 20-28 VAC

Output 1 Box 2

- 1 = Relay: 2A / 240 VAC
- 2 = Pulse DC for SSR drive: 5 VDC (30 mA max)
- 3 = Isolated, 4-20 mA (default), 0-20 mA
- **5** = Isolated VDC, 0-10 scalable
- C = Pulse DC for SSR drive: 14 VDC (40 mA max)

Output 2 / Alarm 1 BOX 3

- $\mathbf{0}$ = None
- 1 = Relay: 2A / 240 VAC
- 2 = Pulse DC for SSR drive: 5 VDC (30 mA max)
- 3 = Isolated, 4-20 mA (default), 0-20 mA
- **5** = Isolated, VDC, 0-10 scalable
- C = Pulse DC for SSR drive: 14 VDC (40 mA max)

Alarm 2 BOX 4

- $\mathbf{0}$ = None
- 1 = Relay: 2A / 240 VAC

Option 1 Box 5

- $\mathbf{0}$ = None
- 1 = RS-485 Interface

Option 2 BOX 6

- 0 = None
- 1 = 2 Event Inputs
- 2 = 1 Event Input and 1 CT Input
- 3 = 2 CT Inputs

Option 3 BOX 7

- $\mathbf{0}$ = None
- 1 = Retransmit: 4-20 mA / 0-20 mA
- 2 = Retransmit: 0-10 VDC
- 3 = Relay: 2A / 240 VAC

Option 4 BOX 8

- 0 = None
- **1** = Terminal Cover



Note: Detailed information on features common to digital microprocessor-based TEC temperature controls and the complete Table of Input Range and Accuracy can be found on page 13-46.

Transformer for Heater Break Alarm (0-50 Amp current) Part Number: TEC99998 Specifications on page 13-47